

NECA SERIES ELECTRONIC RETURN DAMPER ACTUATOR

2 Point Control
10 Nm

NENUTEC[®]

INNOVATIVE MEMBER OF SWISS⁺ TEC

NENUTEC ASIA PACIFIC PTE LTD

7030 Ang Mo Kio Ave 5
#03-56 Northstar @ AMK
Singapore 569 880



(65) 6570 3233



(65) 6570 6783



info@nenutec.com.sg

DAMPER ACTUATOR MODEL CHART

MODEL								
VOLTAGE 230VAC ~ 24VAC/DC	●	●	●	●	●	●	●	●
TORQUE (NM)	2 ; 5 ; 10 ; 20 ; 40	2 ; 5 ; 10 ; 20 ; 40	5 ; 10 ; 20	5 ; 10 ; 20	3 ; 5 ; 8	3 ; 5 ; 8	10 ; 15	5
CONTROL	2/3 pts	Modulating	2 pts	Modulating	2 pts SR	2 pts SR	3 pts	Modulating

SPECIAL TYPE

ELECTRONIC RETURN			●	●				
SPRING RETURN					●			
FIRE & SMOKE SPRING RETURN						●		
SMOKE SAFETY							●	
NETWORKING								●

TYPE DESIGNATION

TYPE	ACTUATOR	DESIGNATION	CONTROL	VOLTAGE	DOT	INPUT SIGNAL	HYPHENATED	TOQUE		AUXILIARY SWITCH
N	A	C	M	1	.	1	-	0	5	S1

TYPE	N = Standard Actuator
	S = Fire & Smoke
ACTUATOR	A = Standard Actuator
	E = Electronic Return
DESIGNATION	C = Standard Actuator
	S = Fast Running Actuator
	F = Spring Back Actuator
CONTROL	A = 2/3 Points
	M = Modulating
VOLTAGE	1 = 24 VAC/VDC
	2 = 230 VAC
	3 = 110/120 VAC
	4 = 48 VAC

INPUT SIGNAL (NOT APPLICABLE FOR 2/3 POINTS)	1 = 0(2)...10 VDC and 0(4)...20 mA	
	2 = 0...10 VDC only	
	3 = 0...135 Ω only	
	4 = 4...20 mA only	
TORQUE	02 = 2 Nm	03 = 3 Nm
	05 = 5 Nm	08 = 8 Nm
	10 = 10 Nm	15 = 15 Nm
	20 = 20 Nm	40 = 40 Nm
AUXILIARY SWITCH / FEEDBACK POTENTIOMETER	None = No Auxiliary or Feedback Potentiometers	
	S1 = 1 x Auxiliary Switch	
	S = 2 x Auxiliary Switches	
	P1 = 1000Ω	
	P2 = 10000Ω	
	P3 = 140Ω	

NECA SERIES

ELECTRONIC RETURN DAMPER ACTUATOR

2 Point Control
10 Nm

NECA...10 SERIES (S1)

NECA series actuators with Electronic Return® (ER) function are designed and produced for extended functionalities in HVAC systems fan coil and laboratory applications. Electronic Return® (ER) is able to manage short voltage interruptions for max. 4 seconds.




PRODUCT FEATURE

- Torque 10 Nm
- Damper size 2.0 m²
- Power supply AC/DC 24V and AC 230V
- Shaft dimensions - Ø 10...20 mm / □ 5...14 mm
- Minimum Shaft Length 40 mm
- Adjustable angle of rotation
- Selectable direction of rotation of reversing actuator
- Actuator with 1 m cable connection
- Optional 1 Adjustable SPDT auxiliary switch
- Manual Over-ride push button

MODEL SELECTION TABLE

MODEL / TYPE	TORQUE	POWER SUPPLY	RUNNING TIME	RETURN	AUXILIARY SWITCH
NECA 1-10	10 Nm	AC/DC 24 V ± 10%	60...80 sec	40 sec	-
NECA 1-10S1	10 Nm	AC/DC 24 V ± 10%	60...80 sec	40 sec	1 x SPDT (Adjustable)
NECA 2-10	10 Nm	AC 230 V ± 10%	60...80 sec	40 sec	-
NECA 2-10S1	10 Nm	AC 230 V ± 10%	60...80 sec	40 sec	1 x SPDT (Adjustable)

DIMENSION (mm)




TECHNICAL SPECIFICATION

MODEL NUMBER	NECA 1-10 (S1)	NECA 2-10 (S1)
TORQUE	10 Nm	10 Nm
DAMPER SIZE	2.0 m ²	2.0 m ²
SHAFT DIMENSION	Ø 10...20 mm / □ 5...14 mm	Ø 10...20 mm / □ 5...14 mm
POWER SUPPLY	AC/DC 24 V ± 10%	AC 230 V ± 10%
FREQUENCY	50...60 Hz	50...60 Hz
CONTROL SIGNAL	2 point control	2 point control
POWER CONSUMPTION		
● OPERATING	7.2 W	7.2 W
● END POSITION	1.2 W	1.2 W
FOR WIRE SIZING	10.0 VA	10.0 VA
ELECTRICAL CONNECTION	1 m Cable	1 m Cable
AUXILIARY SWITCH RATING	3 (1.5) A / AC 250 V	3 (1.5) A / AC 250 V
PROTECTION CLASS	Class II □	Class II □
ANGLE OF ROTATION	90° (95° mechanical)	90° (95° mechanical)
WEIGHT	1.8 Kg	1.8 Kg
LIFE CYCLE	60,000 Rotation	60,000 Rotation
SOUND LEVEL	< 45 dB (A)	< 45 dB (A)
IP PROTECTION	IP54	IP54
OPERATING TEMPERATURE	-20°...50° as per IEC 721-3-3	-20°...50° as per IEC 721-3-3
NON-OPERATING TEMPERATURE	-30°...+60° C / IEC 721-3-2	-30°...+60° C / IEC 721-3-2
AMBIENT HUMIDITY	5%...95% rH non condensing / EN	5%...95% rH non condensing / EN
MAINTENANCE	Maintenance Free	Maintenance Free
MODE OF OPERATION	Type I / EN 60730-1	Type I / EN 60730-1
EMC	CE & ISO 9000 EN / EEC	CE & ISO 9000 EN / EEC

NECA SERIES ELECTRONIC RETURN DAMPER ACTUATOR

2 Point Control
10 Nm

WIRING DIAGRAM NECA...10 (S1) POWER SUPPLY AC/DC 24 V / AC 230V




⚠ Connect via safety isolating transformer


DIRECTION OF ROTATION NECA...10 (S1)

Default factory setting: CW.

Direction of rotation can be change by toggling between CW/CCW switch on the actuator's housing.




WIRING DIAGRAM NECA...10 (S1) AUXILIARY SWITCH




AUXILIARY SWITCH NECA...10 (S1)

Switch **a** factory-set at 5°.

The auxiliary switch can be optimally adjusted between 0°...90°.




WIRING DIAGRAM NECA...10 (S1) PARALLEL CONNECTION




REMARK

Parallel connection of NECA...10 actuators are limited to 5. Power consumption must be observe.

RELEASING THE ADAPTER NECA...10 (S1)



LIMITING ANGLE OF ROTATION NECA...10 (S1)



IMPORTANT REMARK

For special requirement, consult your local Nenutec's representative.



This actuator includes electrical and electronic components and may not be disposed as household garbage. Please consider the local valid legislation.



AC / DC 24 V:
AC 230 V:

Connect via safety isolating transformer.

To isolate from the main power supply, the system must incorporate a device which disconnects the phase conductor (with at least a 3mm contact gap.)

The performance specifications are nominal and conform to acceptable industry standards. NENUTEC shall not be liable for damages resulting from misapplication or misuse of its products.